راهنمای نصب A280A

نصب درايور پرينتر:

ابتدا فایل setup را اجرا میکنید. صفحه ای مثل شکل زیر باز میشود روی دکمه Next کلیک کنید

ne SPEODRIVEN VII	502 1,637,800 1	Packed Type A	Andried CRC32	
		K	The vial maked GARDCOAL Bows Series Protein Driver VII on your computer. It is recommended that you dose all other applications before continuing. Club Parat to continue, or Cancel to well Setup:	
			Cance	

سپس روی گزینه I accept the agreement را کلیک نمایید و مجددا روی دکمه Next کلیک نمایید.

me	Sce Pa	visit Tute Model CECI2	
and the second se		Listater	
GPEDORVEN VLL.	1,637,890 1,630	o 13/ Setup - GAUNCHA IDmm Series Printer Driver V11	
		License Agreement Masse read the following important information before continuing.	
		Please read the following License Agreement. You must accept the terms of this agreement before centerung with the installation.	
		SOFTWARE LIDDINGE AGAESHENT	
		DIFORTANT - READE READ CARDPULLY1 The GADISONA software you are about "" In deveload will be lowned to you, the lownee, on the condition that you agree	
		Pressult allows their adjustments' cooperator, soon value the board of prime TERMS of Thets adjustments' if you by herbitau, board.adub, cooper, die Offetbindtscude thet softmake. If you de not agree to fee there auritation an this agreement, glassic do not instally or download the software. These record the date of download in under the attitude the bindtermenty (00) day seminarity (one begins).	
		l accept the agreement O I do not accept the agreement	
		<8xx (Next) Cancel	

در این پنجره ویندوز سیستم شما به صورت پیش فرض انتخاب شده است سپس روی دکمه ی Install Printer Driver کلیک نمایید.

GPBODRVCH V11. 1637,000 Soze Packed Type Modified CRC32 The folder GPBODRVCH V11. 1637,000 1600 Folder CRC64.Blowne Series Protect Diver V13 Nor 0 Solect OS (666664) Folder OS (666664) Folder OS (666664) Folder OS Folde	Add Latract To	Test View	Delete Find Ward Info ViraScan Commert \$77	
	SU GPRODRUS	UN_VILLOP - ZP arch Size 1.630,000 1/	Packed Jype Modified CRC32 File Folder SOO File Folder SOO File Solder SOO File Solder Soo File Solder For Select OS 666/464) For File Solder SOO C Tindews 37 C Vindews 2003 C Rinders Vista C Vindews 7 C Vindews 2003 C Rinders Vista C Vindews 80 C Vindews 80 Install WD Virtual Serial Part Driver Zastall Printer Driver 80 File and #44 05 Canad	

در این کادر از لیست پرینتر های پرینتر مدل GP5890را انتخاب نمایید و روی دکمه Next کلیک نمایید.

Install Module	GP-80160N(Cut) Series	-	
rinter Setting- ☞ Set Default Printer Name	GP-80160N(No Cut) Series GP-80160N(Cut) Series GP-80220(No Cut) Series GP-80220(Cut) Series GP-80250 Series GP-80250 Series GP-80250 Series GP-80300 Series GP-130160 Series GP-130160 Series GP-130160 Series GP-080250 Series		
	GP-W80300 Series GP-M80300 Series GP-F80300 Series S-W80 Series S-M80 Series S-30xH Series S-30xH Series S-30xF Series		

در صفحه ی بعدی در صورتی که بخواهید روی پورتusb نصب نمایید پورت usb را انتخاب نمایید و دکمه install انتخاب نمایید

Specify Port A port is used Specify the por another port type r	to connect a printer to the computer. t that you are using. If you are connecting using TCP/IP or tot listed below, creat a new port.
Port	Туре
VSB002	Virtual printer port for USB
USB001 192.168.123.100 SHRFAX:	Virtual printer port for USB Standard TCP/IP Port Fax Monitor Port
COM4: FILE:	Local Port Local Port
LPT1: LPT2: LPT3:	Local Port Local Port
1	Create Port Configure Port
li	(Peak Tratall Consul

در صورتی که بخواهید با استفاده از شبکه و Dongle کار نمایید روی گزینه ...Create Port کلیک نمایید

Specify Port A port is use Specify the p another port type	d to connect a printer to the computer. ort that you are using.If you are connect not listed below, creat a new port.	ting using TCP/IP o
Port	Туре	
LPT2:	Local Port	
LPT3:	Local Port	
XPSPort:	Local Port	
COM1:	Local Port	
COM2:	Local Port	
COM3:	Local Port	=
nul:	Local Fort	
COMT:	Local Fort	
	Create Port	Configure Port
I	< Back Instal	1 Cancel

روی گزینه Standard TCP/IP Port کلیک نمایید و دکمه ...New Pprt را انتخاب نمایید.

0	elect Por	rt (x80/x04)			2.5
	Specify	Port			
	Spe	Create Port	weet a princer to the	computer.	/IP or
1	Port	Annilable Part T	free a		
	LPT2: LPT3:	WSD Port	(ype		
-	XPSPo COM1:	Standard ICP/IP	Fort		
	COM2: COM3:	ErSUN Fort Handl	er Monitor		E
	nul: COM7:	-			
	COM6:			-	-
			New Port.	Close	<u> </u>
	L			1 I and the second second second second	
			< Back	Install	Cancel
	This Dr	iver is suitable fo	or Windows x86 and x6	4 OS.	

از پنجره ی با شده روی دکمه Next کلیک نمایید



در صفحه ی بعدی Ip پرینتر را در هر دو کادر وارد نمایید(Ip: 192.168.123.100) و روی دکمه Nextکلیک نمایید

1			
d a port?			
dress, and a port nam	ne for the desired	device.	
192.168.123.100	>]
192.168.123.100			
HERE IP ADDRESS.			
			-
	< Back	Next >	Cance
	Iress, and a port nam 192.168.123.100 192.168.123.100	Iress, and a port name for the desired 192.168.123.100 192.168.123.100 HERE IP ADDRESS. < Back	Iress, and a port name for the desired device.

حتما باید پرینتر روشن باشد تا در این مرحله شناسایی شود

Windows is detecting the TCP/IP port and will move to the next page when finished.
 Detecting the TCP/IP port Windows will automatically move to the next page when the detection is done.

	Add Standard TCP/IP Printer Port Wizard
Pr	Additional port information required The device could not be identified.
	 The device is not found on the network. Be sure that: The device is turned on. The network is connected. The device is properly configured. The address on the previous page is correct. If you think the address is not correct, click Back to return to the previous page. Then c address and perform another search on the network. If you are sure the address is correct
	Oevice Type Generic Network Card
his	(Back Need) Cannel



بعد از نصب پرینتر پیام!Completed نمایش داده میشود

Install Module GP-V80300	Series 💌	
Printer Setting		
🔽 Set Default Printer	INSTROE7	
Pariston Ness CP-190300	-	
	ОК	

در پنجره آخر گزینهFinish را So,I will restart the computer later را انتخاب نمایید و دکمه Finish را کلیک کنید

